

IMAGE COMING SOON

Product Number: 47647

Order Abbreviation: LU400/SUPER5-KIT

General Description: 120/208/240/277/480V 5-tap magnetic core and coil ballast for 400W high pressure sodium lamp

*** Full Case Required**

Product Information

| | |
|-----------------------------------|---------------------------|
| Abbrev. With Packaging Info. | LU400SUPER5KIT 1/CS 1/SKU |
| ANSI Code | S51 |
| Capacitor Diameter | 0 |
| Circuit Type | CWA |
| Nominal Voltage (V) | 120/208/240/277/480V |
| Number of Lamps | 1 |
| Open Circuit Voltage (V) | 190 |
| Power Factor | >0.9 |
| Primary Lamp Type | LU400 |
| Sound Rating | N |
| Starting Method | PULSE IGNITOR |
| Starting Temperature - Fahrenheit | -40°F |
| Starting Temperature - Celsius | -40°C |
| Total Harmonic Distortion (THD) | <20% |
| Wiring Method | LEADS |
| Total Maximum Wattage | 464 |



Footnotes

- Product is a kit containing the core & coil, capacitor, ignitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- High Voltage Pulse Present on Open Circuit
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum Starting Temperature: -40F/-40C.
- Product contains installation instructions