

# IMAGE COMING SOON

**Product Number:** 47737

**Order Abbreviation:** M250/MULTI-KIT

**General Description:** 120/208/240/277V multi-tap magnetic core and coil ballast for 250W metal halide lamp

## Product Information

Abbrev. With Packaging Info.	M250MULTIKIT 1/CS 1/SKU
ANSI Code	M58
Capacitor Height	5"
Circuit Type	CWA
Nominal Voltage (V)	120/208/240/277V
Number of Lamps	1
Open Circuit Voltage (V)	300
Power Factor	>0.9
Primary Lamp Type	M250
Sound Rating	N
Starting Method	OCV
Starting Temperature - Fahrenheit	-22°F
Starting Temperature - Celsius	-30°C
Total Harmonic Distortion (THD)	<20%
Wiring Method	LEADS
Total Maximum Wattage	290



## Footnotes

- Product is a kit containing the core & coil, capacitor, ignitor (where required), brackets and mounting hardware
- Install in accordance with National Electric Codes
- Ground Ballast Core and Metallic Case of Capacitor and Ignitor
- Minimum starting temperature: -20 F / -29 C
- Product contains installation instructions